

NFO Sinus Optimal 2.2kW - One unit for all sizes!

NFO
Sinus

The NFO Sinus frequency inverter is based on a patented Swedish technology that allows you to control the speed of electric motors with rated current 1.0 - 4.9 A without generating electromagnetic interference, which in turn offers a range of unique benefits. Thanks to the sine-wave output voltage, the inverter is interference-free in itself.

SIMPLE

The installation is simple and cost-effective in that the installer does not need shielded cables, EMC filters or other EMC-classified installation accessories. When undertaking renovations or energy efficiency projects, it's possible to re-use existing non-shielded cables, which makes the installation work quick and easy. There is no limit of cable length between the NFO Sinus and the motor, except for the resistance of the cable. The NFO Sinus can be installed where it's suitable depending on the application, even if the distance to the motor is several hundred meters. The unique Sinus technology provides cost-efficient and flexible solutions in all environments.

SILENT

NFO Sinus is interference-free and will therefore not cause any electromagnetic interference with other technical

equipment in its surroundings. The NFO Sinus meets the most stringent requirements according to the EMC directive 2014/30/EU, without filters and without shielded cables, and can be used in all sorts of applications, from industrial to residential areas. With NFO Sinus you also avoid all annoying interference and switching noises in the motor, which results in a quieter environment.

SAFE

NFO Sinus does not generate any bearing currents. The motor therefore has a longer lifespan. No earth leakage currents are generated, which means that residual current devices for both personal safety and fire prevention can be used. This provides a high level of electrical safety.

HIGH PRECISION

The motor speed is very precisely controlled, with full torque right from stand-still as well as at low speed, regardless of chosen control mode: Speed, frequency or process control. Furthermore, the inverter has an energy-save function that allows you to save even more energy when running with a low load on the motor; e.g. fans, which at times run at low speed.



Simple installation

- No shielded cables
- No complicated installation requirements
- No limitations of distance



Silent operation

- No electromagnetic interference
- No irritating switching noise



Safe technology

- No bearing currents
- No earth currents

NFO Sinus Optimal is optimized for AC motors with a rated current of 1.0 to 4.9 A (Max 5.8 A)

NFO Sinus Optimal 2.2kW is optimized for AC motors with a rated current of 1.0 to 4.9 A (max 5.8 A)

Continuous Rating (A)	1.0 - 4.9
Maximum Rating (A)	5.8
Protection Class	IP55
Measurements HxDxW (mm)	390x190x160
Weight (kg)	7.0
Part number	NFO 3A4D3490D



	Voltage (V)	Frequency (Hz)
Input:	3x380-480V ±10%	50/60 Hz ± 10 %
Output:	0-480V +10 %	0-150Hz
Output voltage wave form:	Sinus	
Operating mode:	4-quadrant	
Configurable control signals:		
2 pcs Analog input	0-10V, 2-10V, ±10V, 0-20 mA, 4-20 mA, ±20 mA, Potentiometer	
2 pcs Analog output	0-10V, 2-10V, ±10V, 0-20 mA, 4-20 mA, ±20 mA	
Selectable from terminal, pos or neg. logic	7 fixed setpoints	

Acceleration time:	0.5-100 s
Retardation time:	0.5-100 s
Relay outputs:	Common alarm (Potential free contact max 1A/50V _{DC}) Run indication / Programmable function (Potential free contact max 1A/50V _{DC})
Voltage output:	24V supply to external sensor
Control modes:	Frequency control 0-150 Hz Speed control 0-9000 rpm Process control PI controller with feedback
Local mode:	Forward, Reverse, Stop
Motor protection:	Thermistor input PTC or Klixon Power guard Overload protection
Communication:	Modbus RTU / Modbus ASCII / NFO Classic protocol / USB / RS-485 (native) PROFIBUS / PROFINET / Modbus TCP (using Anybus CompactCom module)
Software:	NFO Sinus Manager, free download from www.nfodrives.se
Energysave function:	Optimizing magnetizing current of motors at low load
Efficiency class CDM:	IE2 according to Ecodesign Regulation 2019/1781
Environment:	Ambient temp -10 - +45°C Storage temp -20 - +60°C Relative Humidity 0 - 90% non-condensing.
Earth current:	< 2 mA. RCD's for both personal and fire protection can be used
EMC:	According to EMC Directive 2014/30/EU Certified to be used without shielded cables and filters
Standards:	EMC Emission EN 55011:2016, EN 55011/A1:2017, EN 61000-3-3:2013 EMC Immunity EN 61000-6-2:2005, EN 61000-4-2, -3, -4, -5, -6, -11 LVD EN 61800-5-1:2017, EN 61800-5-1/A1:2017

Option
Brake resistors/chopper: For dimensioning of braking resistors, see the user and installation manual

For more information: See NFO Drives Operating and installation manual